




**Accessori  
Accessories**



LC 6500 DDC - Z Self Start			
Motore Engine			Generatore Generator
Potenza Power ( HP / 3600 r.p.m. )	13	Carica batteria Charging battery voltage	12 V
Avviamento Start system	manuale elettrico recoil electric	Amperaggio Current	8,3 A
Cilindrata Displacement	389 cc	Frequenza Frequency	50 Hz.
Tipo carburante Fuel	benzina gasoline	Tensione Voltage	230 Volt
Capacità serbatoio Tank capacity	25 lt	Potenza uso continuo Continuous duty power	5 kW
Rumorosità Noise $\leq 7m$ dB(A)	76	Potenza max Max. power	5,5 kW
Servizio continuo orario Continuous duty running time	9 h	Dimensioni Dimensions	L = 680 P = 540 H = 540
Monocilindrico, raffreddamento aria, 4-tempi Single cylinder, forced air cooling, 4-stroke		Peso Weight	90 Kg

### Generatore a benzina

Gruppo elettrogeno monofase con sistema d'avviamento automatico integrato, con motore a scoppio 4 tempi a benzina, flangiato ad un alternatore a 2 poli monofase. Avviamento con autoavvolgente ed elettrico a batteria. Quadro di comando con 2 prese monofase e con caricabatteria 12 volt e scheda carica batteria.

### Gasoline engine generator

Single phase generating set complete with automatic starting system, with 4-stroke gasoline engine coupled to single phase 2-pole alternator. Recoil or electric starter with battery. Control panle with 2 single phase plugs and 12-volt battery-charger and battery charger board.